

marantz®

ER2500S Home Theater System

When you think of Marantz, you think of component systems, with separate pieces for each function. This might imply complexity, but while it's true that big systems consisting of many different boxes can be intimidating, with Marantz components that is never the case. And this point can be emphasized with our home theater systems. These systems couldn't be easier to setup and use and still deliver the performance that Marantz is famous for. With the beautiful ER2500S, you will enjoy true multi-channel performance from all of your music and video. Marantz, a killer Home Theater doesn't have to scare you.

SS2500 6.1 Channel Speaker System Package

- 5 Satellite Speakers and Sub-woofer Setup
- 6.1ch Surround Sound by The Phantom Surround Back Speaker in the Surround L & R Speakers
- Sleek Looking Passive Sub-woofer
- Real Wood Speaker Enclosures

ER2500S Home Theater System

Package consists of the following components: ER2500 Progressive Scan DVD/Receiver and SS2500 6.1ch Speaker system package (5 satellite speakers and Sub-woofer setup). See below for individual product descriptions.



ER2500 Progressive Scan DVD/Receiver

- | | | |
|--|--|---|
| <ul style="list-style-type: none">• 6.1ch DVD/AM/FM Receiver• Silver Finish• 100 Watts x7 in 6 ohm• High Efficiency Digital Amplifier• Plays DVD-Video, DVD-R/RW (Video Mode), SVCD, VCD, CD, CD-R/RW, MP3, WMA and JPEG Discs• Dolby Digital EX, Pro Logic IIx | <ul style="list-style-type: none">• DTS ES® (Discrete 6.1/Matrix 6.1, Neo:6 (Cinema/Music))• Progressive Scan Component Video Output with 3:2 Pull Down Film Detection• 54MHz/10-Bit Video D/A Converter• 192kHz/24-Bit Audio | <ul style="list-style-type: none">• D/A Converters• Powered Sub-woofer Output• Simple Setup Menu• Color Coded Speaker Terminals• NTSC PAL Converter• External A/V Inputs/Output• Digital Audio Inputs/Output• TV Codes Pre-coded System Remote Control |
|--|--|---|



*All specifications, dimensions and weights are subject to change without notice. D&M Holdings, Marantz, Marantz America, Inc. or any of its subsidiaries will not assume any liability for errors within this document.